

AT-GS2002/SP

Ethernet Bridging Converter



AT-GS2002/SP

10/100/1000T, 1000 SFP standalone bridging converter

Overview

The AT-GS2002/SP Ethernet Bridging Converters are designed to extend the distance of your network by interconnecting LAN devices that are physically separated by large distances. These bridging converters have the functionality to connect any managed/unmanaged 10Mbps, 100Mbps, or 1000Mbps (1Gbps) switch or hub using standard 10/100/1000T RJ45 connections and convert the electrical signal to fiber optical signal via its SFP port.

Extend the Distance of Ethernet

Each AT-GS2002/SP bridging converter features a 10/100/1000T twisted pair port and an SFP port. The twisted pair port has an RJ45 connector and a maximum operating distance of 100 meters (328 feet). These units can operate at half- and full-duplex.

The AT-GS2002/SP fiber optic port has a SFP slot and a maximum operating distance is dependent on the SFP.

Standalone or Rackmounted

Each small bridging converter is powered by an external power supply unit for use in standalone applications. Where multiple media converters are used, up to 12 standalone devices can be inserted into a low-cost AT-MCR12 rackmount chassis, allowing all the converters to be powered by a single internal power supply. In critical applications, a second load sharing internal power supply can be installed into the rackmount chassis. The bridging converters can also be 19" rack mounted either individually using the AT-WLMT, AT-TRAY1 or up to four devices using the AT-TRAY4.

Hassle Free Support

All Allied Telesyn Ethernet bridging converters have a limited lifetime warranty and free technical support, ensuring trouble-free installation.

Key Features

- Converts speed as well as media type
- Extends Gigabit networks to distances up to 80km
- Auto MDI/MDI-X
- Auto-negotiation (IEEE 802.3u-compliant)
- Store and forward data packet handling
- Support MissingLink™ and Smart MissingLink™
- Transparent to IEEE 802.1Q VLAN packets
- Automatic address learning and aging
- System and port LEDs
- External AC power adapter
- Rack-mountable using optional AT-WLMT, AT-MCR12, TRAY4, or TRAY1 chassis

Ordering Information

AT-GS2002/SP-xx

Gigabit Ethernet bridging converter, 10/100/1000T to SFP (550m to 80km)

Where xx =

- 10 AC Power supply, US power adapter
- 20 AC Power supply, European power adapter
- 30 AC Power supply, UK power adapter
- 40 AC Power supply, Australian power adapter
- 90 AC Power supply, US FED — US power adapter

AT-SP Series

1000Mbps SFP product line

AT-GS2002/SP | Ethernet Bridging Converter

Technical Specifications

Status Indicators

System LEDs

LED	Colour	Description
Power	Green	Indicates that the converter power is on.
	Off	Indicates that the converter has no power signal.
AN	Green	Indicates that the port Auto-negotiation is ON.
	Off	Indicates that the port Auto-negotiation is OFF.

1000X Port LEDs (SFP port)

LED	Colour	Description
LINK	Green	Indicates a valid link has been established between the port and the end-node.
	Off	Indicates that there is no link between the port and the end-node.
ACT	On	Indicates that the port is transmitting and/or receiving data packets.

10/100/1000T Twisted Pair Port LEDs

LED	Colour	Description
LINK	Green	Indicates a valid link has been established between the port and the end-node.
	Off	Indicates that there is no link/activity between the port and the end-node.
ACT	On	Indicates that the port is transmitting and/or receiving data packets.
	Off	Indicates that there is no activity on the port.
100	Green	Indicates that the port is operating at 100Mbps.
	Off	Indicates that the port is not operating at 100Mbps.

1000	Green	Indicates that the port is operating at 1000Mbps.
	Off	Indicates that the port is not operating at 1000Mbps.

NOTE: The AT-GS2002/SP operates at 10Mbps when both the 100Mbps LED and 1000Mbps LED are OFF.

MODE push button LEDs

LED	Colour	Description
ML	Green	MissingLink mode is enabled.
	Off	MissingLink mode is disabled.
SML	Green	Smart MissingLink mode is enabled.
	Off	Smart MissingLink mode is disabled.
LT	Green	Link Test mode is enabled.
	Off	Link Test mode is disabled.

Link Test, MissingLink, and Smart MissingLink Functions

Link Test

The link test is a fast and easy way for you to test the connections between the media converter ports and the end-nodes that are connected to the ports. If a network problem occurs, you can perform a link test to determine which port is experiencing a problem, and so be able to focus your troubleshooting efforts on the cable or end-node where the problem resides.

MissingLink™

The MissingLink™ feature enables the two ports on the media converter to pass the 'Link' status of their connections to each other. When the media converter detects a loss of connection to an end-node, the media converter shuts down the connection to the other port, thus notifying the end-node that the connection has been lost.

Smart MissingLink™

The Smart MissingLink™ feature performs exactly the same function as MissingLink™ with one additional feature. When a link is lost on a port, the LINK LED of the port which still has a valid connection to its end-node starts to blink. This allows you to quickly determine which port still has a valid connection (LINK LED blinking) and which port has lost its connection (LINK LED off).

Physical Specifications

Dimensions: W x D x H
10.5 cm x 9.5 cm x 2.5 cm
(4.125 in x 3.75 in x 1.0 in)

Weight: 0.27 kg (0.60 lbs)

Power Characteristics

External Power: 100-120/220-240VAC, 50/60Hz
Supply: +/-3%
Input Supply Voltage: 12VDC +/-5%
Max Current : .5A
Power Consumption: 6W

Copper Ports

RJ45 connector
Auto MDI/MDI-X
Half/full-duplex
Auto-negotiation
10/100/1000T compliant

Environmental Specifications

Maximum Operating Temperature: 0°C to 40°C
(32°F to 104°F)
Maximum Storage Temperature: -25°C to 70°C
(-13°F to 158°F)
Operating and Storage Altitude: Up to 3,048 meters (10,000 feet)
Relative Humidity: 5% to 95% (non-condensing)
Operating and Storage:

Electrical/Mechanical Approval

Safety: Conforms to all standards normally supported by Allied Telesyn products including safety standards EN60950 (TUV), UL60950 (cULus), CE Compliant, EN60825
Standard: IEEE 802.3, IEEE 802.3u
Immunity: Conforms to EN55024 immunity standard
EMI/RFI: FCC Class A, EN55022 Class A, VCCI Class A, C-TICK

USA Headquarters | 19800 North Creek Parkway | Suite 200 | Bothell | WA 98011 | USA | T: +1 800 424 4284 | F: +1 425 481 3895

European Headquarters | Via Motta 24 | 6830 Chiasso | Switzerland | T: +41 91 69769.00 | F: +41 91 69769.11

Asia-Pacific Headquarters | 11 Tai Seng Link | Singapore | 534182 | T: +65 6383 3832 | F: +65 6383 3830

www.alliedtelesyn.com

© 2005 Allied Telesyn Inc. All rights reserved. Information in this document is subject to change without notice. All company names, logos, and product designs that are trademarks or registered trademarks are the property of their respective owners. 617-000035 Rev. C