

# Cisco 10GBASE Dense Wavelength-Division Multiplexing XFP Modules

## Product Overview

The Cisco® Dense Wavelength-Division Multiplexing (DWDM) XFP pluggable module (Figure 1) allows enterprise companies and service providers to provide scalable and easy-to-deploy 10 Gigabit LAN or WAN services in their networks.

**Figure 1.** Cisco DWDM XFP Module



Main features of the Cisco DWDM XFP include:

- The Cisco DWDM XFP supports 10-Gigabit data rates from 9.9G to 11.1G.
- The hot-swappable input/output device plugs into an Ethernet XFP port of a Cisco switch or router to link the port with the network.
- The Cisco DWDM XFP supports the Cisco quality identification (ID) feature, which enables a Cisco switch or router to identify whether or not the module is an XFP module certified and tested by Cisco.
- The standard Cisco DWDM XFP supports 32 nontunable ITU 100-GHz wavelengths.
- The tunable Cisco DWDM XFP supports 80 tunable ITU 50-GHz wavelengths.
- Cisco DWDM XFP modules supports digital optical monitoring capability.

## Platform Support

The Cisco DWDM XFPs are supported across a variety of Cisco switches, routers, and optical transport devices. For more details, refer to the Cisco 10-Gigabit transceivers compatibility matrix at:

[http://www.cisco.com/en/US/docs/interfaces\\_modules/transceiver\\_modules/compatibility/matrix/OL\\_6974.pdf](http://www.cisco.com/en/US/docs/interfaces_modules/transceiver_modules/compatibility/matrix/OL_6974.pdf)

## Connectors and Cabling

- Equipment: standard XFP interface
- Network: dual LC/PC connector

**Note:** Only connections with patch cords with PC or UPC connectors are supported. Patch cords with APC connectors are not supported. All cables and cable assemblies used must be compliant with the standards specified in the standards section.

## Dimensions

- Dimensions (L x W x H): 71 x 18.5 x 8.5 mm. Cisco XFPs typically weigh less than 300 grams.
- Environmental Conditions and Power Requirements.
- Operating temperature range: 32 to 158°F (0 to 70°C).
- Storage temperature range: -40 to 185°F (-40 to 85°C).
- The maximum power consumption per Cisco XFP module is 3.5W.

## Optical Parameters

Table 1 shows the main optical characteristics for the standard non-tunable Cisco DWDM XFP modules.

**Table 1.** Optical Parameters for standard DWDM XFP

Parameter	Symbol	Minimum	Typical	Maximum	Units	Notes and Conditions
<b>Transmitter</b>						
Spectral width				0.2	nm	Full width, -20 dB from maximum, with resolution bandwidth (RBW) = 0.01 nm
Transmitter center wavelength		x - 100	x	x + 100	pm	Refer to Table 2 for center wavelengths
Side-mode suppression ratio	SMSR	30			dB	
Transmitter extinction ratio	OMI	9			dB	
Transmitter optical output power	P <sub>out</sub>	-1.0		3.0	dBm	Average power coupled into single-mode fiber
<b>Receiver</b>						
Receiver optical input wavelength		1530		1565	nm	
Receiver damage threshold				4.0	dBm	
Dispersion tolerance		-500		1600	ps/nm	
<b>Power-Limited Performance (measured at optical signal-to-noise ratio [OSNR] of 30 dB at 0.1-nm RBW)</b>						
Optical input power	P <sub>in</sub>	-23.0		-7.0	dBm	See footnote *
Dispersion power penalty				3	dB	See footnote *
<b>Noise-Limited Performance (measured at OSNR of 24 dB at 0.1-nm RBW)</b>						
Optical input power	P <sub>in</sub>	-18.0		-7.0	dB	See footnote *
Dispersion OSNR penalty				3	dB	See footnote *

\* At bit error rate (BER) = 1E-12 with IEEE802.3 test pattern.

### Note:

1. Parameters are specified over temperature and at end of life unless otherwise noted.
2. When shorter distances of single-mode fiber are used, an inline optical attenuator (10-dB) must be used to avoid overloading and damaging the receiver.

Table 2 shows the main optical characteristics for the tunable Cisco DWDM XFP modules.

**Table 2.** Optical Parameters for tunable DWDM XFP

Parameter	Symbol	Minimum	Typical	Maximum	Units	Notes and Conditions
<b>Transmitter</b>						
Spectral width				0.2	nm	Full width, -20 dB from maximum, with resolution bandwidth (RBW) = 0.01 nm
Transmitter center wavelength		x - 25	X	x + 25	Pm	Refer to Table 3 for center wavelengths
Side-mode suppression ratio	SMSR	30			dB	
Transmitter extinction ratio	Omi	9			dB	
Transmitter optical output power	Pout	0.0		3.0	dBm	Average power coupled into single-mode fiber
<b>Receiver</b>						
Receiver optical input wavelength		1530		1565	nm	
Receiver damage threshold				4.0	dBm	
Dispersion tolerance		-500		1600	ps/nm	
<b>Receiver Power Performance</b>						
		<b>Units</b>		<b>Range</b>	<b>Notes and Conditions</b>	
<b>Long Wavelength Performances C Band NO-FEC Applications Power-Limited</b>						
<b>Input power range</b>		dBm		-7 to -24	At BER=10e-12 applicable at 9.9G and 10.3G, 30dB OSNR (0.1nm RBW)	
<b>Input power range</b>		dBm		-7 to -22	At BER=10e-12 (-500 to +1600 ps/nm) applicable at 9.9G and 10.3G, 30dB OSNR (0.1nm RBW)	
<b>Long Wavelength Performances C Band NO-FEC Applications Noise-Limited</b>						
<b>Input power range</b>		dBm		-7 to -22	At BER=10e-12 applicable at 9.9G and 10.3G, 26dB OSNR (0.1nm RBW)	
<b>Input power range</b>		dBm		-7 to -20	At BER=10e-12 (-500 to +1600 ps/nm) applicable at 9.9G and 10.3G, 26dB OSNR (0.1nm RBW)	
<b>Long Wavelength Performances C Band FEC Applications Noise-Limited</b>						
<b>Input power range</b>		dBm		-7 to -18	At BER PREFEC <10e-5 applicable at 10.7G and 11.1G, 15.5dB OSNR (0.1nm RBW)	
<b>Input power range</b>		dBm		-7 to -18	At BER PREFEC <10e-5 (-500 to +1000 ps/nm) applicable at 10.7G and 11.1G, 17dB OSNR (0.1nm RBW)	
<b>Long Wavelength Performances C Band E-FEC Applications Power-Limited</b>						
<b>Input power range</b>		dBm		-7 to -27	At BER PREFEC <7 <sup>-10</sup> e-4 applicable at 10.7G and 11.1G, 26dB OSNR (0.1nm RBW)	
<b>Input power range</b>		dBm		-7 to -26	At BER PREFEC <7 <sup>-10</sup> e-4 (-500 to +1300 ps/nm) applicable at 10.7G and 11.1G, 26dB OSNR (0.1nm RBW)	
<b>Long Wavelength Performances C Band E-FEC Applications Noise-Limited</b>						
<b>Input power range</b>		dBm		-7 to -20	At BER PREFEC <7 <sup>-10</sup> e-4 applicable at 10.7G and 11.1G, 12dB OSNR (0.1nm RBW)	
<b>Input power range</b>		dBm		-7 to -20	At BER PREFEC <7 <sup>-10</sup> e-4 (-500 to +1300 ps/nm) applicable at 10.7G and 11.1G, 14dB OSNR (0.1nm RBW)	

**Note:**

- Parameters are specified over temperature and at end of life unless otherwise noted.
- When shorter distances of single-mode fiber are used, an inline optical attenuator (10-dB) must be used to avoid overloading and damaging the receiver.

Table 3 shows the 80 DWDM ITU-50GHz channels the device can be tuned to.

**Table 3.** ITU 50-GHz center wavelengths and channel numbering

Channel Id	Frequency (THz)	Wavelength (nm)	Channel Id	Frequency (THz)	Wavelength (nm)
80	195.9	1530.33	79	195.85	1530.72
78	195.8	1531.12	77	195.75	1531.51
76	195.7	1531.90	75	195.65	1532.29
74	195.6	1532.68	73	195.55	1533.07
72	195.5	1533.47	71	195.45	1533.86
70	195.4	1534.25	69	195.35	1534.64
68	195.3	1535.04	67	195.25	1535.43
66	195.2	1535.82	65	195.15	1536.22
64	195.1	1536.61	63	195.05	1537.00
62	195.0	1537.40	61	194.95	1537.79
60	194.9	1538.19	59	194.85	1538.58
58	194.8	1538.98	57	194.75	1539.37
56	194.7	1539.77	55	194.65	1540.16
54	194.6	1540.56	53	194.55	1540.95
52	194.5	1541.35	51	194.45	1541.75
50	194.4	1542.14	49	194.35	1542.54
48	194.3	1542.94	47	194.25	1543.33
46	194.2	1543.73	45	194.15	1544.13
44	194.1	1544.53	43	194.05	1544.92
42	194.0	1545.32	41	193.95	1545.72
40	193.9	1546.12	39	193.85	1546.52
38	193.8	1546.92	37	193.75	1547.32
36	193.7	1547.72	35	193.65	1548.11
34	193.6	1548.51	33	193.55	1548.91
32	193.5	1549.32	31	193.45	1549.72
30	193.4	1550.12	29	193.35	1550.52
28	193.3	1550.92	27	193.25	1551.32
26	193.2	1551.72	25	193.15	1552.12
24	193.1	1552.52	23	193.05	1552.93
22	193.0	1553.33	21	192.95	1553.73
20	192.9	1554.13	19	192.85	1554.54
18	192.8	1554.94	17	192.75	1555.34
16	192.7	1555.75	15	192.65	1556.15
14	192.6	1556.55	13	192.55	1556.96
12	192.5	1557.36	11	192.45	1557.77
10	192.4	1558.17	9	192.35	1558.58
8	192.3	1558.98	7	192.25	1559.39

Channel Id	Frequency (THz)	Wavelength (nm)	Channel Id	Frequency (THz)	Wavelength (nm)
6	192.2	1559.79	5	192.15	1560.20
4	192.1	1560.61	3	192.05	1561.01
2	192.0	1561.42	1	191.95	1561.83

## Warranty

Standard warranty: 90 days.

## Ordering Information

Table 4 gives details about ordering Cisco DWDM XFPs.

**Table 4.** Cisco DWDM XFP Ordering Information

Product Number	Description	ITU Channel
DWDM-XFP-60.61=	10GBASE-DWDM 1560.61 nm XFP (100-GHz ITU grid)	21
DWDM-XFP-59.79=	10GBASE-DWDM 1559.79 nm XFP (100-GHz ITU grid)	22
DWDM-XFP-58.98=	10GBASE-DWDM 1558.98 nm XFP (100-GHz ITU grid)	23
DWDM-XFP-58.17=	10GBASE-DWDM 1558.17 nm XFP (100-GHz ITU grid)	24
DWDM-XFP-56.55=	10GBASE-DWDM 1556.55 nm XFP (100-GHz ITU grid)	26
DWDM-XFP-55.75=	10GBASE-DWDM 1555.75 nm XFP (100-GHz ITU grid)	27
DWDM-XFP-54.94=	10GBASE-DWDM 1554.94 nm XFP (100-GHz ITU grid)	28
DWDM-XFP-54.13=	10GBASE-DWDM 1554.13 nm XFP (100-GHz ITU grid)	29
DWDM-XFP-52.52=	10GBASE-DWDM 1552.52 nm XFP (100-GHz ITU grid)	31
DWDM-XFP-51.72=	10GBASE-DWDM 1551.72 nm XFP (100-GHz ITU grid)	32
DWDM-XFP-50.92=	10GBASE-DWDM 1550.92 nm XFP (100-GHz ITU grid)	33
DWDM-XFP-50.12=	10GBASE-DWDM 1550.12 nm XFP (100-GHz ITU grid)	34
DWDM-XFP-48.51=	10GBASE-DWDM 1548.51 nm XFP (100-GHz ITU grid)	36
DWDM-XFP-47.72=	10GBASE-DWDM 1547.72 nm XFP (100-GHz ITU grid)	37
DWDM-XFP-46.92=	10GBASE-DWDM 1546.92 nm XFP (100-GHz ITU grid)	38
DWDM-XFP-46.12=	10GBASE-DWDM 1546.12 nm XFP (100-GHz ITU grid)	39
DWDM-XFP-44.53=	10GBASE-DWDM 1544.53 nm XFP (100-GHz ITU grid)	41
DWDM-XFP-43.73=	10GBASE-DWDM 1543.73 nm XFP (100-GHz ITU grid)	42
DWDM-XFP-42.94=	10GBASE-DWDM 1542.94 nm XFP (100-GHz ITU grid)	43
DWDM-XFP-42.14=	10GBASE-DWDM 1542.14 nm XFP (100-GHz ITU grid)	44
DWDM-XFP-40.56=	10GBASE-DWDM 1540.56 nm XFP (100-GHz ITU grid)	46
DWDM-XFP-39.77=	10GBASE-DWDM 1539.77 nm XFP (100-GHz ITU grid)	47
DWDM-XFP-38.98=	10GBASE-DWDM 1538.98 nm XFP (100-GHz ITU grid)	48
DWDM-XFP-38.19=	10GBASE-DWDM 1538.19 nm XFP (100-GHz ITU grid)	49
DWDM-XFP-36.61=	10GBASE-DWDM 1536.61 nm XFP (100-GHz ITU grid)	51
DWDM-XFP-35.82=	10GBASE-DWDM 1535.82 nm XFP (100-GHz ITU grid)	52
DWDM-XFP-35.04=	10GBASE-DWDM 1535.04 nm XFP (100-GHz ITU grid)	53
DWDM-XFP-34.25=	10GBASE-DWDM 1534.25 nm XFP (100-GHz ITU grid)	54
DWDM-XFP-32.68=	10GBASE-DWDM 1532.68 nm XFP (100-GHz ITU grid)	56
DWDM-XFP-31.90=	10GBASE-DWDM 1531.90 nm XFP (100-GHz ITU grid)	57
DWDM-XFP-31.12=	10GBASE-DWDM 1531.12 nm XFP (100-GHz ITU grid)	58
DWDM-XFP-30.33=	10GBASE-DWDM 1530.33 nm XFP (100-GHz ITU grid)	59
DWDM-XFP-C	10GBASE-DWDM tunable XFP (50-GHz ITU grid)	See table 3

## Regulatory and Standards Compliance

### Standards

- GR-20-CORE: Generic Requirements for Optical Fiber and Optical Fiber Cable
- GR-326-CORE: Generic Requirements for Single-Mode Optical Connectors and Jumper Assemblies
- GR-1435-CORE: Generic Requirements for Multifiber Optical Connectors

### Safety

- Laser Class I 21CFR1040
- Network Equipment Building Standards (NEBS) Level 3

## For More Information

For more information about Cisco 10GBASE DWDM XFP modules, contact your sales representative.



**Americas Headquarters**  
Cisco Systems, Inc.  
San Jose, CA

**Asia Pacific Headquarters**  
Cisco Systems (USA) Pte. Ltd.  
Singapore

**Europe Headquarters**  
Cisco Systems International BV Amsterdam,  
The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at [www.cisco.com/go/trademarks](http://www.cisco.com/go/trademarks). Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)