

# 1 Port PCI Express IDE Controller Adapter Card

StarTech ID: PEX2IDE



This PCI Express IDE Controller Adapter Card provides a cost-effective way to use legacy drives with modern computers, by converting a PCI Express port into an IDE port.

Providing data burst transfer rates of up to 133MBps and support for PIO 0/1/2/3/4 and UDMA 33/66/100/133 operating modes, the IDE controller card offers an efficient way to add an IDE channel with support for two IDE drives on the same channel.

A complete dual profile solution, the PCI Express IDE controller card provides both standard and low profile brackets for adapting to slimline or small form factor system applications.

# **Applications**

- Add an additional IDE port to a computer system
- Replace a failed IDE port
- Add an IDE port for connecting legacy ATA devices such as old hard drives and tape drives

#### **Features**

- 2-channel IDE port supports two drives
- 48-bit LBA support
- Supports ATA/ATAPI commands
- Supports UDMA 6 mode which supports transfer rates up to 133 MBps
- Includes a low profile installation bracket





## **Technical Specifications**

Warranty Lifetime

Ports 1

Interface IDE

Bus Type PCI Express

Card Type Standard Profile (LP bracket incl.)

Chipset ID JMicron - JMB368

Connector Type(s) 1 - PCI Express x1 Male

Internal Ports 1 - IDE (40 Pin; EIDE/PATA) Male

LBA support 48-bit

OS Compatibility Windows® 8 / 8.1 (32/64bit), 7 (32/64), Vista (32/64), XP (32/64), 2000

Windows® Server 2012, 2008 R2

System and Cable Requirements Available PCI Express expansion slot

Shipping (Package) Weight 0.4 lb [0.2 kg]

Included in Package 1 - PCI Express IDE Controller Card

Included in Package 1 - IDE Cable

Included in Package 1 - Low Profile Bracket Included in Package 1 - Instruction Manual

### Certifications, Reports and Compatibility









